

iiyama - LoopSign Deployment Guide

Deployment of LoopSign to your Iiyama display is very easy. LoopSign utilizes its Android app on Iiyama's custom Android OS to play content.



Connecting the display to ethernet is always highly recommended, but wifi connections will usually work as well, given a strong and stable wifi connection.



Content


1.	Go through the first-time setup menu	2
2.	Check date/time settings and install the LoopSign player app	4
2.1	Date & time settings	4
2.2	Install the LoopSign Player app.....	7
2.3	Set LoopSign Player as the Custom app	9
3.	Set automatic on/off for the display and launch LoopSign	11
3.1	Set schedule for automatic on/off	11
3.2	Launch the LoopSign Player app.....	13
4.	Enroll the display on your LoopSign account	14

1. Go through the first-time setup menu

When booting the display for the first time, you have to go through Iiyama's first-time setup menu. There you'll set language and network, before being asked to clone setup files from SD card or USB. Skip this step by pressing the right arrow button on the remote. Skip the Signage settings as well in the next step, before making sure to set the *Auto power off* setting to *off* in the final Power Settings step.










2. Check date/time settings and install the LoopSign player app

2.1 Date & time settings

Press the Home button on the remote and enter the Android launcher. From here, enter the Settings app and navigate to System → Date & time, and then enable automatic syncing and set the correct time zone.










2.2 Install the LoopSign Player app

Download the LoopSign Player app either directly on the screen using the built-in browser or download it to your computer and put it on a memory stick (FAT32 recommended) which you can connect to the screen.

Download link: <https://loop24.no/lspdm.apk>


Open the Storage app from the screen's Android launcher, and from there find and install the LoopSign Player app file.








2.3 Set LoopSign Player as the Custom app

Open the Settings app from the screen's Android launcher and navigate to Signage display → Source settings → Custom app. Select LoopSign Player in the pop-up menu.







3. Set automatic on/off for the display and launch LoopSign

3.1 Set schedule for automatic on/off


Press the Home button on the remote and navigate to Advanced option → Schedule. Set your preferred for when the display should automatically turn on and off, as shown in the below example picture. (Remember to set Custom as the startup input.)







3.2 Launch the LoopSign Player app



The last step of the setup is to switch to the Custom input of the display, to launch the LoopSign Player app. After a couple of seconds, your display's unique hash code will show, which you will use to enroll your display to your LoopSign account.





4. Enroll the display on your LoopSign account

Log in to LoopSign, and then click *Manage Screens*. After that, click *Devices* in the top menu. In the Devices overview, click *+Enroll* to add the display to your LoopSign account, using the hash code showing on the display. After that you can assign the display to a LoopSign screen to immediately have your display start playing your LoopSign content.







Congratulations! You've now successfully configured your display, enrolled it to your LoopSign account and assigned it to play content from a LoopSign screen.

