



**How to set up
Philips 10BDL3051T
LoopMeeting**

Step-1 – Configure Network

Enter Android setup by pressing “Enter” and “Volume –“ fast right after each other.
(The top button on the left side is “Enter” and the lowest button is “Volume –“
Default password to enter Android setup is 1-2-3-4

By default the Philips is set up to use network by cable.

If you will use network by cable and DHCP the you do not need to change network settings.

If you want to use wireless network connection, then configure it by pressing the “Network” Icon and press the “Wi-Fi” Icon to configure Wireless network settings.

Step-2 – Configure language and timezone

Configure setting by pressing the “Settings” icon

Set Language and timezone to the settings that fits your environment.

Make sure the time/date settings are correct – otherwise Exchange will refuse connection.

Step-3 – Install LoopMeeting App

Make sure to have the LoopMeeting app on a USB stick mounted in one of the USB ports.

Press the “App’s” icon to enter applications.

Select “Filemanager”

Select the folder MNT, USB_Storage, USB_Disk1

Install the LoopMeeting app by selecting the APK file.

Go back to main App menu

Step-4 – Autostart LoopMeeting App in kiosk mode.

Select “Settings”, then select “Signage Display” (Skiltvisning if you have chosen Norwegian language)

Select input, then Custom App

Go back to “Signage Display” menu and select “Custom App”

Press “Select App” and choose LoopMeeting.

Now everything is set.